

IEEE-1284 Parallel Interface cable

Signal Funtion	Bit Name	DB-25 M 1284A Pin #	Centronics M 1284B Pin #
nStrobe	<u>C0</u>	1	1
Data Bit 0	D0	2	2
Data Bit 1	D1	3	3
Data Bit 2	D2	4	4
Data Bit 3	D3	5	5
Data Bit 4	D4	6	6
Data Bit 5	D5	7	7
Data Bit 6	D6	8	8
Data Bit 7	D7	9	9
nAck	S6	10	10
Busy	<u>S7</u>	11	11
PaperEnd	S5	12	12
Select	S4	13	13
nAutoLF	<u>C1</u>	14	14
nError (nFault)	S3	15	32
nInit	C2	16	31
nSelectIn	<u>C3</u>	17	36
Grnd Rtn		18	19
Grnd Rtn		19	20
Grnd Rtn		19	21
Grnd Rtn		20	22
Grnd Rtn		20	23
Grnd Rtn		21	24
Grnd Rtn		21	25
Grnd Rtn		22	26
Grnd Rtn		22	27
Grnd Rtn		23	29
Grnd Rtn		24	28
Grnd Rtn		25	30
Ch. Grnd			17
Perif. Hi.			18
Unused			15
Unused			33
Unused			34
Unused			35